

# Bosch B/G Series Alarm System Instructions

## Arming and Disarming Your System

### **To arm (turn on) your system:**

The keypad must say "READY TO ARM." If this message appears on the keypad, enter your four-digit code on the keypad and then push the "ENT" (enter) key.

Your arming/disarming codes are: \_\_\_\_\_

\_\_\_\_\_

The keypad will then show "ALL SECURE, EXIT NOW." You will hear the keypad

beep. You have \_\_\_\_\_ seconds to exit. Open the delay door and exit.

Your delay door is located at: \_\_\_\_\_.

Please note: All doors must be closed when arming the system.

### **To disarm (turn off) your system:**

When entering the building, enter through the delay door **ONLY**.

Upon opening the door you will hear a beeping sound, this is the pre-alarm. You have \_\_\_\_\_ seconds in which to enter the four-digit code to turn the system off. Enter your four-digit code and press the ENT (enter) button.

### **If alarm occurs:**

Put in your **Code + Enter**. This will silence the alarm. Check the zones that went into alarm, which is displayed by the keypad. Once you have checked them, go back to the keypad and push **Enter + Your Code + Enter**. This will clear the system out so you may continue to arm and disarm.

## **Bypassing A Point**

Bypassing a point:

1. Open the Main menu.
2. Press [On/Off] to open the menu.
3. Press [Bypass] to open the menu.
4. Press [Bypass Points] to open the menu.
5. Select a point to bypass.
6. Escape from the menu.

## **Unbypass Points**

Unbypassing a point returns a bypassed point to the security system so that it can once again respond to trouble and alarm conditions.

Unbypassing a point:

1. Open the Main menu.
2. Press [On/Off] to open the menu.
3. Press [Bypass] to open the menu.
4. Press [Unbypass Points] to open the menu.
5. Select a point to unbypass.
6. Escape from the menu.

